

PATENT
450100-03502

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

APPLICATION FOR LETTERS PATENT

TITLE: DATA TRANSMITTING AND RECEIVING
APPARATUS AND DATA TRANSMITTING AND
RECEIVING METHOD

INVENTORS: Shinya MASUNAGA, Yoshikatsu NIWA

William S. Frommer
Registration No. 25,506
FROMMER LAWRENCE & HAUG LLP
745 Fifth Avenue
New York, New York 10151
Tel. (212) 588-0800

2025-09-03 10:00:00

DATA TRANSMITTING AND RECEIVING APPARATUS AND DATA
TRANSMITTING AND RECEIVING METHOD

BACKGROUND OF THE INVENTION

Field of the Invention

5 The present invention relates to a data
transmitting and receiving apparatus and a data
transmitting and receiving method, in particular, to
those suitable for a network system that complies with
for example IEEE (The Institute of Electrical and
10 Electronics Engineers) 1394 high performance serial bus
standard (hereinafter referred to as IEEE 1394
standard).

Description of the Related Art

15 So far, as a bus standard for transferring
multimedia data at high speed and on real time, IEEE
1394 standard is known. Because of easy handling of
the IEEE 1394 standard, there is a large expectation
for home networks.

20 In the IEEE 1394 standard, with two types of
systems that are daisy chain and node branch, devices
of up to 63 nodes and up to 16 hops can be connected.

25 In addition, the IEEE 1394 standard defines
three communication speeds S100 (98.304 [Mbps]), S200
(196.608 [Mbps]), and S400 (393.216 [Mbps]). The IEEE
1394 standard defines a 1394-port that has an upper
transfer speed so that the port has a compatibility
with a lower transfer speed. Thus, each node can

transfer data to a destination node at the maximum transfer speed that is common in all nodes on the bus.

Moreover, the IEEE 1394 standard allows a cable to be connected or disconnected and the power of a node to be turned on or off while another node is operating in the above-described connection state. In the IEEE 1394 standard, when a node is added or deleted, the topology of nodes is automatically restructured and node IDs are reassigned.

Fig. 1 shows structural elements and protocol architecture of an interface that complies with the IEEE 1394 standard. As is clear from Fig. 1, the interface that complies with the IEEE 1394 standard can be divided into three functional blocks that are hardware 1, firmware 2, and software 3.

In this case, the hardware 1 is composed of a physical layer (PHY layer) 1A and a link layer 1B. The physical layer 1A directly drives a signal that corresponds to the IEEE 1394 standard. The link layer 1B has a host interface and an interface with the physical layer 1A.

The firmware 2 is composed of a transaction layer 2A and a management layer 2B. The transaction layer 2A is composed of a management driver that performs a real operation for an interface that complies with the IEEE 1394 standard. The management layer 2B is composed of a management driver referred to

as SBM (Serial Bus Management). The management driver complies with the IEEE 1394 standard.

The software 3 is mainly composed of an application layer 3A. The application layer 3A is composed of user software and management software. The management software interfaces with the transaction layer 2A and the management layer 2B.

In the IEEE 1394 standard, a transfer operation performed in a network is referred to as sub action. The IEEE 1394 standard defines two sub actions that are asynchronous transfer mode (this mode is referred to as asynchronous) and isochronous transfer mode that assures a transfer bandwidth (this mode is referred to as isochronous). In addition, each sub action is divided into three parts that are arbitration, packet transmission (data transfer), and acknowledge. In the isochronous transfer mode, the acknowledgement is omitted.

In the asynchronous transfer mode, data is asynchronously transferred. Fig. 2 shows chronological transition states in the asynchronous transfer mode. In Fig. 2, each node monitors the period of the first sub action gap (t_1 to t_2) that is a bus idle state so as to determine whether data has been transferred as the preceding session and data can be transferred as the next session.

When an idle state takes place for a

predetermined time period after data flows on the bus,
a node that needs to transfer data determines that the
bus can be used and starts arbitration (t_2 to t_3) for
obtaining the bus use right. Figs. 3A and 3B show an
5 example of connections of a plurality of nodes.

In Figs. 3A and 3B, a node referred to as root denoted
by "A" determines to which node the bus use right is
given. In Figs. 3A and 3B, "A", "B", "C", "D", and "E"
represent nodes.

10 When a node is given the bus use right in the
arbitration, the node executes a packet transmission
(t_3 to t_4) as a data transfer (t_3 to t_4). After data
has been transferred, the node that has received the
data sends back reception acknowledgement reply code
15 Ack corresponding to the received result (t_5 to t_6) so
as to execute acknowledgement. When the
acknowledgement is executed, the nodes on the
transmission side and the reception side can know that
data has been correctly transferred with the reception
20 acknowledgement reply code Ack.

Thereafter, a sub action gap (namely, the bus
idle state) takes place. In the state, the data
transfer operation is repeated.

On the other hand, in the isochronous
25 transfer mode, as shown in Fig. 4, data is transferred
basically in the same format as the asynchronous
transfer mode. However, the data transfer in the

isochronous transfer mode has higher priority than the data transfer in the asynchronous transfer mode. The data transfer in the isochronous transfer mode (hereinafter referred to as isochronous transfer) is performed after a CSP (Cycle Start Packet) issued by a cycle master node (normally, a root node) at intervals of around 8 [kHz]. As a result, in the isochronous transfer mode, the transfer bandwidth is assured. Consequently, real time data can be transferred.

When a plurality of nodes simultaneously perform the isochronous transfer for real time data, channel IDs are assigned to transfer data of each node so as to distinguish the contents of the transfer data. Corresponding to a pertinent channel ID, a node on the reception side can receive required data.

In the IEEE 1394 standard, data is addressed corresponding to a CSR (Control and Status Register) architecture defined in IEEE 1212 standard. As shown in Fig. 5B, the CSR architecture has an address space of 64 bits. The high order 16 bits represent a destination node, whereas the low order 48 bits represent a memory space of the node.

The high order 10 bits of the 16 bits for the destination node are a bus ID, whereas the low order 6 bits thereof are a node ID. Thus, in the IEEE 1394 standard, except for broadcast addresses (all bits of an ID are 1) of the bus ID and the node ID, up to 1023

buses can be represented. Up to 63 nodes can be connected to each bus.

On the other hand, in the IEEE 1394 standard, when the number of nodes is increased or decreased or when a node issues an initialization request, a bus reset signal is propagated on the bus. When a node receives the bus reset signal, the node removes the current topology information, successively performs three phases of bus initialize, tree identify, and self identify, and structures new topology information.

In this case, in the bus initialize phase, each node recognizes the state of the local port (namely, to which node the local port is connected and whether the local portion is not connected to any node). In addition, each node determines whether it is a leaf (connected to one node) or a branch (connected to two or more nodes).

In the tree identify phase, each port transmits an identification signal to other nodes connected each other so as to determine the relation of parent and child of each port.

In reality, a node (referred to as first node) that has a plurality of ports and of which the status of only one port has not been determined transmits TX_PARENT_NOTIFY state to another node (referred to second node) through a port connected thereto. When the second node receives

TX_PARENT_NOTIFY state from the first node, the second node treats the port as a child port (that means that the port is connected to a child node when viewed from the port). The second node transmits TX_CHILD_NOTIFY state to the first node. When the first node receives TX_CHILD_NOTIFY state, the first node treats the port as a parent node (that means that the port is connected to a parent node when viewed from the port) and determines the relation of parent and child of the nodes. This operation is repeated. As a result, a node that is a parent of all nodes of the bus (namely, one node that has only child ports) is determined. In the IEEE 1394 standard, this node is referred to as root. As was described above (see Figs. 3A and 3B), the root has a function for permitting a packet to be transmitted to all other nodes.

In the self identify phase, the root successively gives a transmission permission to individual nodes in the ascending order of port numbers corresponding to the leaf priority rule. When a node is given the transmission permission, the node successively transmits the self ID packet to the entire bus. As a result, the node ID is determined and the topology of the bus is uniquely determined.

After the three phases have been executed, a packet can be transmitted on the bus. As a result, a node that needs to transmit a packet can issue a

transmission request to the root. At that point, a node that manages a resource necessary for transmitting a data packet in the isochronous transfer mode (hereinafter, the data packet is referred to as isochronous packet) is also determined. This node is referred to as IRM (Isochronous Resource Manager).

The IRM is a node that can become an IRM and that has the largest node ID. Normally, the IRM is the same as the root. A node that becomes an IRM should be provided with three registers that are

CHANNELS_AVAILABLE register, BANDWIDTH_AVAILABLE register, and BUS_MANAGER_ID register. On the bus, a node that needs to transmit an isochronous packet requests the IRM for the desired channel and bandwidth. Only when the desired channel and bandwidth are available, the node can transmit an isochronous packet.

In reality, a node that needs to transmit an isochronous packet issues a read quadrate transaction that is a read request for data of one quadrate (4 [bytes]) to CHANNELS_AVAILABLE register and BANDWIDTH_AVAILABLE register of the IRM and obtains the contents thereof. When the desired channel and bandwidth are available, corresponding to the remaining result, the node issues COMPARE & SWAP as a lock transaction that is a data rewrite request to CHANNEL_AVAILABLE register and BANDWIDTH_AVAILABLE register and rewrites the contents thereof. Only when

the operation can be successfully completed, the node can transmit an isochronous packet on the bus.

However, several problems have been pointed out on the above-described IEEE 1394 standard.

5 The first problem is in that the number of nodes connected to a bus is limited. In the IEEE 1394 standard, 16 bits are assigned to addresses of nodes. However, since it is assumed that communications are made on the same bus, actually, only 63 nodes are connected on the bus. Thus, in a large system that requires many devices (nodes), the IEEE 1394 standard cannot be directly applied.

10 The second problem is in that the initialization due to a bus reset causes the bus transfer efficiency to deteriorate. In other words, in 15 the IEEE 1394 standard, when the number of nodes is increased or decreased or when an initialization request is issued, a bus reset signal is transmitted. Thereafter, the initializing process is performed. 20 However, it will take around 250 [is] after the bus reset is recognized until the arbitration for transmitting a new packet is started. During this period, the bus cannot transfer a packet at all.

25 The time period of 250 [is] is equivalent to two transfer cycles in the above-described isochronous transfer mode. When packets are not transmitted in the time period, part of a picture or sound may be lost.

Thus, the time period may adversely affect a data transfer on real time.

As a means for shortening the bus reset time period, a function referred to as short bus reset is defined in IEEE 1394a - 2000 standard (hereinafter referred to as IEEE 1394a standard) that was standardized for correcting and implementing the IEEE 1394 standard and for defining additional functions thereto. When such a function is used, the bus reset time period can be shortened to around 80 [is].

However, even with such a function, data transfer is suspended for 80 [is]. In addition, when the bus has a node that does not comply with the IEEE 1394a standard, the function cannot be used.

The third problem is in that the bus resource is wasted. Since the IEEE 1394 standard is a standard on a bus, a packet that a particular node transmits is broadcast to the entire bus. Thus, when a packet transfer is performed in such a manner that a small number of nodes require much resource (in particular, an isochronous transfer is performed), it may adversely affect a packet transfer performed between other nodes.

As a method for solving the problems on the IEEE 1394 standard, a 1394-bus bridge has been proposed. The 1394-bus bridge standardizes a function and a protocol for propagating data between buses. Between two buses (hereinafter, each bus is referred to

as local bus), it is necessary to dispose at least one 1394-bus bridge (this bridge is hereinafter referred to as bridge). The bridge is composed of at least two 1394-nodes each of which has a special function referred to as portal. Each portal performs a process for a local bus connected thereto and a process for another local bus connected to another portal that composes the bridge.

Fig. 6 shows an example of the structure of a network system using such a bridge. Referring to Fig. 6, the network system is composed using a bridge 12 having two portals 11A and 11B. A circular portion that connects the local buses 13A and 13B is a bridge, whereas semicircular portions are portals.

In addition, as shown in Fig. 7, when inter-bus connections are also used with 1394-bridges 12₁ to 12₃, up to 1023 but as the maximum number of nodes defined in the standard can be connected. Local buses 13₁ to 13₄ have independent functions of the 1394-buses. When a bus reset and an unnecessary packet that take place on the other local buses 13₁ to 13₄ are filtered by portals 11A₁ to 11A₃ and 11B₁ to 11B₃, a problem of which a bus reset suspends a packet transfer and a problem of which the resource is wasted can be solved. In the following description, for simplicity, it is assumed that the bridge 12 is composed of two portals 11A and 11B. However, it should be noted that

the subject matter of the present invention is not limited to two portal bridges.

At present, the 1394-bridge standard is standardized by P1394.1WG. The contents of the 1394-
5 bridge standard have been published as a draft. Fig. 8 shows the typical structure of a bridge recited in draft 0.08 P17 of P1394. 1. For simplicity, in Fig. 8, similar portions to those in Fig. 6 are denoted by similar reference numerals.

10 A bridge 12 is composed of two portals 11A and 11B. Each of the portals 11A and 11B functions as an independent node that complies with the IEEE 1394 standard. The portals 11A and 11B exchange data with
15 other nodes 14A and 14B (see Fig. 6) of the local buses 13A and 13B (see Fig. 6) using physical layers 20A and 20B, link layers 21A and 21B, and transaction layers 22A and 22B connected to the local buses 13A and 13B (see Fig. 6), respectively. When necessary, the
20 portals 11A and 11B transmit (forward) data to the other local buses 13B and 13A through isochronous transfer mode FIFOs (First-In First-Out) 24A and 24B, asynchronous transfer mode response FIFOs 25A and 25B, or request FIFOs 26A and 26B of an internal bus 23, respectively. The structures of the physical layers
25 20A and 20B, the link layers 21A and 21B, and the transaction layers 22A and 22B of the portals 11A and 11B are the same as those shown in Fig. 1.

Portal controls 27A and 27B have a function of the SBM layer 2B (see Fig. 1) that complies with the IEEE 1394 standard. In addition, each of the portal controls 27A and 27B is provided with a special register and a special table that accomplish the function of the bus bridge that complies with the IEEE 1394 standard. The portal controls 27A and 27B know the topologies of the local buses 13A and 13B connected thereto, respectively. The portal controls 27A and 27B create a routing table 28 corresponding to the entire state of the network. Corresponding to the routing table 28, it is determined whether or not a stream packet is forwarded through the bridge 12.

Using the FIFOs 24A and 24B in the isochronous transfer mode, the bridge 12 can transmit and receive a stream packet through the bridge 12. The P1394. 1 draft practically recites a method for transmitting and receiving a stream packet between the local buses 13A and 13B through the bridge 12. Next, the stream data transmitting and receiving method recited in the draft will be described.

Each of the portals 11A and 11B that can forward stream data through the bridge 12 is provided with a stream routing table that corresponds to the number of streams that each of the portals 11A and 11B can handle at the same time. In the following description, as shown in Fig. 8, it is assumed that the

portal controls 27A and 27B is provided with stream routing tables 31A and 31B, respectively.

Entries of each of the stream routing tables 31A and 31B correspond to STREAM_CONTROL [0] to
5 STREAM_CONTROL [n]. In addition, STREAM_CONTROL entries correspond to streams that are forwarded. A portal that has n STREAM_CONTROL entries can forward n streams through the bridge 12 at the same time.

10 The total number of STREAM_CONTROL entries is stored in a STREAM field of a Bridge_Capabilities entry of a configuration ROM 28 (see Fig. 8). Entries of the portal 11A correspond to those of the portal 11B. In other words, a stream that is received using a
15 STREAM_CONTROL [i] entry of one of the portals 11A and 11B (for example, the portal 11A) is transmitted using a STREAM_CONTROL [i] entry of the other portal (for example, the portal 11B).

Fig. 9 shows a format of a STREAM_CONTROL entry. In Fig. 9, an "st" field F1 represents the
20 status of the portal 11A or 11B. As shown in Fig. 10, when the value of the "st" field F1 is "1", it represents a reception state (Listener). When the value of the "st" field F1 is "2" or "3", it represents a transmission state (Talker).

25 In Fig. 9, a "channel" field F2 represents a channel number of a stream that is transmitted or received. The "channel" field F2 is valid only when

the value of the "st" field F1 is not "0". When the portal 11A or 11B is in the reception state, the "channel" field F2 represents a channel number of a stream received from the local bus 13A or 13B, respectively. Otherwise, the "channel" field F2 represents a channel number of a stream transmitted to the local bus 13A or 13B. The channel number may be changed when the stream passes through the bridge 12.

In Fig. 9, an "i" field F3 represents that stream data is in the isochronous transfer mode (this stream data is referred to as isochronous stream). When stream data is in the asynchronous transfer mode (this stream data is referred to as asynchronous stream), the value of the "i" field F3 is "0". In Fig.9, a "rsv" field F6 is reserved for a future extension.

In Fig. 9, an "spd" field F4 represents the transmission speed of stream data when the value of the "st" field F1 is "2" or "3". Fig. 11 shows the relation between values of the "spd" field F4 and transmission speeds of stream data. In Fig. 9, an "overhead" field F5 represents a specially assigned bandwidth besides a bandwidth assigned to the size of a packet of an isochronous stream. The bandwidth in the isochronous transfer mode (this bandwidth is referred to as isochronous bandwidth) is represented as bandwidth allocation unit in the IEEE 1394 standard.

One "bandwidth allocation unit" represents a time period for which data of one quadrate (4 [bytes]) is transferred at a speed of S1600. One "bandwidth allocation unit" is around 20 [ns].

In Fig. 9, a "payload" field F7 represents the maximum number of quadrates contained in one packet of the stream. The value of the "payload" field F7 does not include the size of the header and CRC (Cyclic Redundancy Check).

The portal control layer requests the IRM for a required bandwidth corresponding to the values of the "spd" field F4, the "overhead" field F5, and the "payload" field F7.

In reality, the portal control layer requests the BANDWIDTH_AVAILABILITY register and the CHANNEL_AVAILABLE register of the IRM for the "bandwidth allocation unit : BWU" (that is given by the following expression) and the channel number that is used.

$$BWU = 512 + (\text{payload} + 3) \times 2^{(4 - \text{spd})}$$

(when overhead is 0)

$$BWU = \text{overhead} \times 32 + (\text{payload} + 3) \times 2^{(4 - \text{spd})}$$

(when overhead is not 0) ... (1)

where "payload", "spd", and "overhead" represent the values of the fields F4, F5, and F7, respectively.

In the above-described method, a stream can be transmitted and received through the bridge 12 (see

Fig. 6) without a problem. In addition, a stream can be transmitted and received to/from the portals 11A and 11B connected to the local buses 13A and 13B (see Fig. 6) without a problem.

Next, an example of which stream data is transmitted and received through the bridge 12 will be described.

As shown in Fig. 12, when stream data is transmitted from a node 14A on one local bus 13A to a node 14B on another local bus 13B, corresponding to a particular situation, it is necessary to rewrite STREAM_CONTROL entries of portals 11A and 11B connected to the local buses 13A and 13B, respectively.

In such a situation, a node that controls the stream (in this example, the node 14A) accesses the portals 11A and 11B and accesses the IRMs of the local buses 13A and 13B to which the portals 11A and 11B are connected so as to obtain the channels and bandwidths for the data transfer. Thereafter, the node 14A accesses the portals 11A and 11B and rewrites STREAM_CONTROL [i] entries of the portals 11A and 11B in their pertinent states.

When stream data is transmitted with channel number "1" and at a communication speed of S100, as shown in Fig. 12, the node 14A sends to the portal 11A a message that causes "0x1 (Listener)" to be set to the "st" field F1 of the corresponding STREAM_CONTROL [i]

entry of the portal 11A (see Fig. 9), "0x1" to the "channel" field F2 thereof, and values corresponding to the speed, size, and type of the stream to the fields F3 to F7 thereof.

5 In addition, the node 14A sends to the other portal 11B a message that causes "0x2 (Talker)" to be set to the "st" field F1 of the corresponding STREAM_CONTROL [i] entry of the other portal 11B, "0x2" to the "channel" field F2 thereof, and values corresponding to speed, size, and type of the stream to the fields F3 to F7 thereof.

10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
22

13B is not considered.

Thus, when such stream data were handled, in the conventional method, STREAM_CONTROL entries could not be properly set. As a result, stream data could not be transmitted to a designated destination. In addition, when the STREAM_CONTROL entries were set in the above-described method, stream data that is transmitted or received to/from the local bus 13A would be adversely affected.

In addition, as shown in Fig. 14, in the conventional IEEE 1394 standard, the case of which stream data is transmitted from a node 14A on a local bus 13A to a portal 11B through a portal 11A connected to the local bus 13A is not considered. Thus, when such stream data were handled, using the defined method, STREAM_CONTROL entries could be properly set. As a result, stream data could not be received by a designated destination. In addition, when the STREAM_CONTROL entries were set in the above-described method, unexpected stream data would be transmitted to the local bus 13B. As a result, the data transfer bandwidth of the local bus 13B would be wasted.

Thus, in a network system that complies with the IEEE 1394 standard, when data can be transmitted and received between the portal 11A connected to the local bus 13A and the node 14B on the local bus 13B and data can be transmitted and received between the node

14A on the local bus 13A and the portal 11B connected to the 13B, the functionality of the entire network system will be improved.

5 OBJECTS AND SUMMARY OF THE INVENTION

 The present invention is made from the above-described point of view. An object of the present invention is to propose a data transmitting and receiving apparatus and a data transmitting and receiving method that allow the functionality of the entire network system to be improved.

10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
 To solve such a problem, a first aspect of the present invention is a data transmitting and receiving apparatus for transmitting and receiving data between an external device and a pertinent bus of a plurality of buses connected by a bridge, the external device forming one portion of the bridge, the data transmitting and receiving apparatus comprising a storing means for storing first information and second information, the first information representing whether the transmission source or the transmission destination of the data is the data transmitting and receiving apparatus, the second information representing whether or not to the data should be transmitted to the pertinent bus, a setting means for setting the first information and the second information stored in the storing means to a predetermined state corresponding to

an external request, and a transmitting and receiving means for transmitting and receiving the data to/from the pertinent bus or the external device corresponding to the first information and the second information stored in the storing means.

As a result, according to the data transmitting and receiving apparatus, data can be transmitted and received in such a manner that the data transmitting and receiving apparatus is a transmission source or a transmission destination without affecting data that is transmitted and received on a bus to which the data transmitting and receiving apparatus is connected depending on the settings of the first information and the second information.

A second aspect of the present invention is a data transmitting and receiving method for transmitting and receiving data between an external device and a pertinent bus of a plurality of buses connected by a bridge, the external device forming one portion of the bridge, the data transmitting and receiving method comprising the steps of storing first information and second information, the first information representing whether the transmission source or the transmission destination of the data is a local device, the second information representing whether or not to the data should be transmitted to the pertinent bus and setting the first information and the second information that

have been stored to a predetermined state corresponding to an external request, and transmitting and receiving the data to/from the pertinent bus or the external device corresponding to the first information and the second information that have been set.

As a result, according to the data transmitting and receiving method, data can be transmitted and received in such a manner that a local device is a transmission source or a transmission destination without affecting data that is transmitted and received on a bus to which the data transmitting and receiving apparatus is connected depending on the settings of the first information and the second information.

These and other objects, features and advantages of the present invention will become more apparent in light of the following detailed description of a best mode embodiment thereof, as illustrated in the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a schematic diagram showing the concept of structural elements and a protocol architecture of an interface that complies with the IEEE 1394 standard;

Fig. 2 is a schematic diagram showing the concept for explaining an asynchronous transfer;

Figs. 3A and 3B are schematic diagrams showing the concept for explaining an acquisition of a bus use right using arbitration;

Fig. 4 is a schematic diagram showing the concept for explaining an isochronous transfer;

Figs. 5A and 5B are schematic diagrams for explaining an address assignment in a CSR architecture;

Fig. 6 is a schematic diagram showing the concept of a basic structure of a 1394-network using a 1394-bridge;

Fig. 7 is a schematic diagram showing the concept of an example of the structure of the 1394-network using a plurality of 1394-bridges;

Fig. 8 is a block diagram showing the structure of two portal bridges;

Fig. 9 is a schematic diagram showing the concept of a format of a STREAM_CONTROL entry;

Fig. 10 is a table showing statuses of an "st" field of the STREAM_CONTROL entry;

Fig. 11 is a table showing the relation between values and data speeds of an "spd" field of the STREAM_CONTROL entry;

Fig. 12 is a schematic diagram showing the concept of transmission and reception of stream data through a local bus;

Fig. 13 is a schematic diagram showing the concept for explaining stream data transmitted from a

portal through an internal bus;

Fig. 14 is a schematic diagram for explaining a flow of stream data received by a portal;

Fig. 15 is a block diagram showing the structure of an IEEE 1394 network system according to an embodiment of the present invention;

Fig. 16 is a block diagram showing the structure of a bridge according to the embodiment;

Fig. 17 is a table showing operations of a portal corresponding to the value of a "p" bit according to the present invention;

Fig. 18 is a table showing operations of a portal corresponding to the value of an "id" bit according to the present invention;

Fig. 19 is a schematic diagram showing the concept for explaining a flow of stream data according to the present invention;

Fig. 20 is a schematic diagram showing the concept for explaining a flow of stream data according to the present invention; and

Fig. 21 is a schematic diagram showing the concept for explaining a flow of stream data according to the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Next, with reference to the accompanying drawings, an embodiment of the present invention will

be described.

(1) Structure of Network System according to Embodiment

In Fig. 15, reference numeral 40 represents a network system according to the present invention. The network system 40 complies with the IEEE 1394 standard. The network system 40 is composed of a first local bus 41A, a second local bus 41B, and a bridge 42 in such a manner that the first local bus 41A and the second local bus 41B are connected through the bridge 42. The bridge 42 complies with the IEEE 1394 standard.

In Fig. 16, similar portions to those in Fig. 8 are denoted by similar reference numerals. Referring to Fig. 16, the bridge 42 is composed of a first portal 43A, a second portal 43B, and an internal bus 23 in such a manner that the first portal 43A and the second portal 43B that are connected to the first local bus 41A and the second local bus 41B, respectively, are connected to each other through the internal bus 23.

The first portal 43A has a physical layer 20A, a link layer 45A, a transaction layer 22A, a portal control 46A, and an application layer (not shown). The application layer functions as a 1394-node. Likewise, the second portal 43B has a physical layer 20B, a link layer 45B, a transaction layer 22B, a portal control 46B, and an application layer (not shown). The application layer functions as a 1394-

node.

In the first portal 43A and the second portal 43B, stream data received through the first local bus 41A and the second local bus 41B is supplied to the link layers 45A and 45B through the physical layers 20A and 20B, respectively. The link layers 45A and 45B extract stream data whose destination is the link layers 45A and 45B from the received stream data, respectively. In addition, corresponding to stream routing tables 31A and 31B that the portal controls 46A and 46B have, the link layers 45A and 45B extract stream data to be forwarded to the second local bus 41B and the first local bus 41A from the received stream data, respectively.

In the first portal 43A and the second portal 43B, stream data that has been extracted by the link layer 45A and the link layer 45B and whose destination is the first portal 43A and the second portal 43B is successively stored to isochronous receiving FIFOs (not shown) of the link layers 45A and 45B, respectively. When necessary, the stream data is sent to the application layers (not shown). On the other hand, in the first portal 43A and the second portal 43B, stream data to be forwarded to the second local bus 41B and the first local bus 41A is transmitted to the second portal 43B and the first portal 43A through the internal bus 23, respectively.

On the other hand, in the second portal 43B and the first portal 43A, the stream data is received by the link layers 45B and 45A, respectively.

When necessary, in the second portal 43B and the first portal 43A, for example channel number converting processes are performed by the link layers 45B and 45A corresponding to the pertinent STREAM_CONTROL [i] entries of the stream routing tables 31B and 31A that the portal controls 46A and 46B have, respectively. Thereafter, the resultant data is transmitted to the second local bus 41B and the first local bus 41A to which the second portal 43B and the first portal 43A are connected through the physical layers 20B and 20A, respectively.

In such a manner, in the network system 40, stream data is transmitted and received between the first local bus 41A and the second local bus 41B through the bridge 42.

In addition to such a structure, in the network system 40, each of the first portal 43A and the second portal 43B has a first bit for determining whether or not the transmission source or the transmission destination of stream data to be transmitted or received is the first portal 43A or the second portal 43B and a second bit for determining whether or not the stream data should be transmitted to the first local bus 41A or the second local bus 41B to

which the first portal 43A or the second portal 43B are connected, respectively.

In other words, as shown in Fig. 17, in the network system 40, bit 15 of the "rsv" field F (see Fig. 9) of the STREAM_CONTROL entry shown in Fig. 9 is defined as a bit "p" for determining whether or not the transmission source or the transmission destination of stream data to be transmitted or received is the local portal. In addition, as shown in Fig. 18, bit 16 of the "rsv" field F6 is defined as a bit "id" for determining whether or not the stream data should be transmitted to the first local bus 41A and the second local bus 41B to which the first portal 43A and the second portal 43B are connected, respectively.

As shown in Fig. 19, when a request for transmitting data is transmitted from the node 44A on the first local bus 41A to the second portal 43B on the second local bus 41B, the portal controls 46A and 46B of the first portal 43A and the second portal 43B set the pertinent STREAM_CONTROL [i] entries in the same manner as stream data is forwarded. In addition, the portal control 46B of the second portal 43B sets "0x1" (that represents that the destination of the stream data is the second portal 43B) to the "p" field of the pertinent STREAM_CONTROL [i] entry of the portal control 46B and "0x1" (that represents that the stream data is not transmitted to the second local bus 41B) to

the "id" field thereof.

Thereafter, stream data whose destination is the second portal 43B and that has been transmitted from the node 44A to the first local bus 41A is transmitted to the second portal 43B through the internal bus 23 by the link layer 45A of the first portal 43A corresponding to the pertinent STREAM_CONTROL [i] entry that the portal control 46A of the first portal 43A has.

Since the "p" field of the pertinent STREAM_CONTROL [i] entry that the portal control 46B of the second portal 43B has is "0x1", the link layer 45B of the second portal 43B that has received the stream data determines that the destination of the stream data is the second portal 43B and stores the stream data to the stream receiving FIFO. On the other hand, since the "id" field of the pertinent STREAM_CONTROL [i] entry is "0x1", the link layer 45B determines that the stream data should not be transmitted to the second local bus 41B. Thus, the link layer 45B does not transmit the stream data to the physical layer 20B.

Thus, the second portal 43B can properly receive stream data whose destination is itself. In addition, stream data that is not received by the node 44b can be prevented from being transmitted from the second portal 43B to the second local bus 41B.

Using such a function, the same stream data

can be transmitted from the node 44A on the first local bus 41A to the second portal 43B, the node 44B other than the second portal 43B on the second local bus 41B, and another node routed through the second local bus 41B.

When the portal controls 46A and 46B of the first portal 43A and the second portal 43B receive such requests, the portal controls 46A and 46B sets the pertinent STREAM_CONTROL [i] entries in the same manner as stream data is forwarded. In addition, the portal control 46B of the second portal 43B sets "0x1" (that represents that the destination of the stream data is the second portal 43B) to the "p" field of the pertinent STREAM_CONTROL [i] entry of the portal control 46B and bit "0x0" (that represent that the data stream should be transmitted to the second local bus 41B) to the "id" field thereof.

As a result, stream data whose destination is the portal 42B and that has been transmitted from the node 44A to the first local bus 41A is forwarded to the second portal 43B through the internal bus 23 by the link layer 45A of the first portal 43A corresponding to the pertinent STREAM_CONTROL [i] entry that the portal control 46A of the first local bus 41A has.

Since the "p" field of the pertinent STREAM_CONTROL [i] entry that the portal control 46B has is "0x1", the link layer 45B of the second portal

43B that has received the second portal 43B determines that the destination of the stream data is the second portal 43B and stores the stream data to the stream receiving FIFO of the link layer 45B. In addition, since the "id" field of the pertinent STREAM_CONTROL [1] entry is "0x0", the link layer 45B determines that the stream data should be transmitted to the second local bus 41B and transmits the stream data to the physical layer 20B. As a result, the stream data is transmitted to the second local bus 41B through the physical layer 20B. The stream data is transmitted to the destination node 44B on the second local bus 41B and another destination node routed through the second local bus 41B.

In such a manner, in the network system 40, the first portal 43A and the second portal 43B can receive stream data from the second local bus 41B and the first local bus 41A connected to the second portal 43B and the first portal 43A that compose the bridge 42, respectively. In addition, when the "p" field and the "id" field of the pertinent STREAM_CONTROL [1] entry are set corresponding to the tables shown in Figs. 17 and 18, the present invention can be applied for a 1394-bridge and a 1394-portal that do not comply with the present invention without losing the compatibility of their operations.

On the other hand, as shown in Fig. 20, when

the first portal 43A transmits stream data to the node 44b on the second local bus 41B or when the first portal 43A transmits stream data to another node routed through the second local bus 41B, the portal control 46A of the first portal 43A sets the pertinent STREAM_CONTROL [i] entry thereof in the same manner as stream data is forwarded. In addition, the portal control 46B sets the pertinent STREAM_CONTROL [i] entry thereof in the same manner as stream data is received.

In addition, the portal control 46A of the first portal 43A sets "0x2 (Talker)" or "0x3 (Talker)" (that represents that the first portal 43A transmits stream data) to the "st" field of the pertinent STREAM_CONTROL [i] entry thereof, "0x1" (that represents that the stream data is transmitted to the internal bus) to the "p" field thereof, "0x1" (that represents that the stream data is not transmitted to the first local bus 41A) to the "id" field thereof. However, in this case, when a block allows the destination of stream data to be uniquely identified, the "st" field may be "0x1 (Listener)".

Thus, stream data generated by the first portal 43A is transferred by the first portal 43A itself corresponding to the pertinent STREAM_CONTROL [i] entry that corresponds to the channel number.

Actually, since the "p" field of the pertinent STREAM_CONTROL [i] entry that the portal

control 46A has is "0x1", the link layer 45A of the first portal 43A transmits the stream data to the second portal 43B through the internal bus 23. In addition, since the "id" field is "0x1", the link layer 45A determines that the stream data should not be transmitted to the first local bus 41A. Thus, the link layer 45A does not transmit the stream data to the physical layer 20A.

When the link layer 45B of the second portal 43B has received the steam data through the internal bus 23, the link layer 45B transmits the stream data to the second local bus 41B corresponding to the pertinent STREAM_CONTROL [i] entry of the portal control 46B of the second portal 43B.

Thus, the first portal 43A can transmit the stream data from the second portal 43B through the internal bus 23. In addition, stream data that is not received by any node on the first local bus 41A can be prevented from being transmitted from the first portal 43A.

Using such a function, the same steam data as that the second portal 43B receives can be transmitted to the node 44A other than the first portal 43A on the first local bus 41A and another node routed through the first local bus 41A.

Actually, the portal control 46A of the first portal 43A sets the pertinent STREAM_CONTROL [i]

entries of the first portal 43A and the second portal 43B in the same manner as stream data is forwarded. In addition, the portal control 46A of the first portal 43A sets bit "0x1" (that represents that the destination of the stream data is the internal bus 23) to the "p" field of the pertinent STREAM_CONTROL [i] entry thereof and bit [0x0] (that represents that the stream data is transmitted to the first local bus 41A) to the "id" field thereof.

Thus, in the same manner as described above, stream data generated by the first portal 43A is successively sent from the first portal 43A to the second local bus 41B through the internal bus 23 and the second portal 43B. In addition, since the "id" field of the pertinent STREAM_CONTROL [i] entry of the first portal 43A is "0x0", the stream data is transmitted to the first local bus 41A.

Thus, unlike with the conventional network system, in the network system 40, stream data can be transmitted from the first local bus 41A or the second local bus 41B connected to the first portal 43A or the second portal 43B that composes the bridge 42 to the second portal 43B or the first portal 43A, respectively. In addition, corresponding to the tables shown in Figs. 17 and 18, when predetermined values are to the "p" field of the pertinent STREAM_CONTROL [i] entry and the "id" field thereof, the same stream data

can be transmitted to the first local bus 41A or the second local bus 41B without need to considering the destination of the stream data is the internal bus 23, the first local bus 41A, or the second local bus 41B. Thus, with the common STREAM_CONTROL entries, stream data can be transmitted.

In addition, as shown in Fig. 21, when the first portal 43A needs to transmit stream data to the second portal 43B that composes the bridge 42 along with the first portal 43A, the portal control 46A of the first portal 43A sets "0x1" to the "p" field of the pertinent STREAM_CONTROL [i] entry thereof and "0x1" to the "id" field thereof. In addition, the portal control 46A accesses the second portal 43B and sends to the second portal 43B a message that causes "0x1" and "0x1" to be set to the "p" field and the "id" field of the pertinent STREAM_CONTROL [i] entry that the portal control 46B of the second portal 43B has.

Thus, stream data that is generated by the first portal 43A is transferred by the first portal 43A itself corresponding to the pertinent STREAM_CONTROL [i] entry.

Actually, since the "p" field of the pertinent STREAM_CONTROL [i] entry is "0x1", the link layer 45A of the first portal 43A determines that the destination of the stream data is the internal bus 23 and transmits the stream data to the second portal 43B

through the internal bus 23. On the other hand, since the "id" field is "0x1", the link layer 45A determines that the stream data should not be transmitted to the first local bus 41A. Thus, the link layer 45A does not transmit the stream data to the physical layer 20A.

In addition, since the "p" field of the pertinent STREAM_CONTROL [i] entry of the portal control 46B of the second portal 43B is "0x1", the link layer 45B of the second portal 43B that has received the stream data through the internal bus 23 determines that the destination of the stream data is the second portal 43B and stores the stream data to the local stream receiving FIFO of the link layer 45B. On the other hand, since the "id" field of the pertinent STREAM_CONTROL [i] entry is "0x1", the link layer 45B determines that the stream data should not be transmitted to the second local bus 41B. Thus, the link layer 45B does not transmit the stream data to the physical layer 20B.

In such a manner, in the network system 40, stream data can be properly transmitted and received between the first portal 43A and the second portal 43B. In addition, stream data that is not received by any node on the first local bus 41A and the second local bus 41B connected to the first portal 43A and the second portal 43B can be prevented from being transmitted, respectively.

(2) Operation and Effect of Embodiment

In the above-described structure, in the network system 40, bit 15 of the "rsv" field F6 (see Fig. 9) of the pertinent STREAM_CONTROL entry of each of the first portal 43A and the second portal 43B that compose the bridge 42 is defined as a bit "p" for determining whether or not the transmission source or the transmission destination of stream data to be transmitted or received is the first portal 43A or the second portal 43B. In addition, bit 16 of the "rsv" field F6 is defined as a bit "id" for determining whether or not the stream data should be transmitted to the first local bus 41A and the second local bus 41B to which the first portal 43A and the second portal 43B are connected, respectively. The "p" field and the "id" field are set corresponding to the transmission and reception formats of desired stream data.

Thus, in the network system 40, stream data can be transmitted and received between the node 44A on the first local bus 41A or the node 44b on the second local bus 41B and the second portal 43B or the first portal 43A and between the first portal 43A or the second portal 43B and the node 44B on the second local bus 41B or the node 44A on the first local bus 41A without affecting data stream transmitted and received to/from the first local bus 41A or the second local bus 41B.

According to the above-described structure,
bit 15 of the "rsv" field F6 of the pertinent
STREAM_CONTROL entry of each of the first portal 43A
and the second portal 43B that compose the bridge 42 is
used as a bit "p" for determining whether data stream
to be transmitted or received is the first portal 43A
or the second portal 43B. In addition, bit 16 of the
"rsv" field F6 is used as a bit "id" for determining
whether or not the stream data should be transmitted to
the first local bus 41A and the second local bus 41B to
which the first portal 43A and the second portal 43B
are connected, respectively. Thus, stream data can be
transmitted and received between the node 44A on the
first local bus 41A or the node 44b on the second local
bus 41B and the second portal 43B or the first portal
43A and between the first portal 43A or the second
portal 43B and the node 44b on the second local bus 41B
or the node 44A on the first local bus 41A without
affecting stream data transmitted and received to/from
the first local bus 41A and the second local bus 41B.
Thus, a network system that allows stream data to be
properly transmitted and received and the functionally
to be improved can be accomplished.

(3) Another Embodiment

In the above-described embodiment, the case
of which the present invention is applied for the
network system 40 of which the first local bus 41A and

the second local bus 41B are connected through the
bridge 42 was described. However, the present
invention is not limited to such a case. In other
words, the present invention can be applied for a
network of which three or more local buses are
connected through a bridge.

In the above-described embodiment, the case
of which the bridge 42 is a two-port bridge was
described. However, the present invention is not
limited to such a case. In other words, the present
invention can be applied for the case of which a bridge
is composed of three or more portals.

In the above-described embodiment, as first
information that represents whether or not the
transmission source or the transmission destination of
data is a local portal and second information that
represents whether or not data should be transmitted to
a pertinent bus, bit 15 ("p" field) and bit 16 ("id"
field) of the "rsv" field F6 (see Fig. 9) of the
pertinent STREAM_CONTROL entry are used. However, the
present invention is not limited to such an example.
In other words, flags corresponding to bit 15 and bit
16 of the "rsv" field of the pertinent STREAM_CONTROL
entry may be provided. Moreover, in addition to bit 15
and bit 16 of the "rsv" field of the pertinent
STREAM_CONTROL entry, such flags can be provided. In
addition, as the first information and the second

information, other than bits and flags may be used.

In the above-described embodiment, the case of which first information that represents whether the transmission source or the transmission destination of data is the local portal (in the embodiment, the first information is the "p" field of the pertinent STREAM_CONTROL entry) and second information that represents whether or not data should be transmitted to a pertinent bus (in the embodiment, the second information is the "id" field of the pertinent STREAM_CONTROL entry) are stored as a storing means in the portal control 46A and the portal control 46B, respectively, was described. However, the present invention is not limited to such a case. In other words, according to the present invention, such information may be stored in for example a configuration ROM 29 other than the portal control 46A and the portal control 46B or in the link layer 45A of the first portal 43A and the link layer 45B of the second portal 43B.

In the above-described embodiment, as setting means for setting first information and second information corresponding to an external request, the portal control 46A and the portal control 46B are used. However, the present invention is not limited to such an example. In other words, various types of setting means such as a memory driver and link layers 45A and

45B can be used depending on the storage locations for the first information and the second information.

According to the above-described embodiment, corresponding to the values of the "p" field and the "id" field of the pertinent STREAM_CONTROL entry, as transmitting and receiving means for transmitting and receiving stream data to/from the first local bus 41A and the second local bus 41B or external devices (in the above-described embodiment, the second portal 43B and the first portal 43A), the link layer 45A and the link layer 45B are used. However, the present invention is not limited to such an example. In other words, corresponding to the structure of the data transmitting and receiving apparatus of the present invention, such functions can be provided to corresponding structural portions.

The first aspect of the present invention is a data transmitting and receiving apparatus for transmitting and receiving data between an external device and a pertinent bus of a plurality of buses connected by a bridge, the external device forming one portion of the bridge, the data transmitting and receiving apparatus comprising a storing means for storing first information and second information, the first information representing whether the transmission source or the transmission destination of the data is the data transmitting and receiving apparatus, the

second information representing whether or not to the data should be transmitted to the pertinent bus, a setting means for setting the first information and the second information stored in the storing means to a predetermined state corresponding to an external request, and a transmitting and receiving means for transmitting and receiving the data to/from the pertinent bus or the external device corresponding to the first information and the second information stored in the storing means. As a result, according to the data transmitting and receiving apparatus, data can be transmitted and received in such a manner that the data transmitting and receiving apparatus is a transmission source or a transmission destination without affecting data that is transmitted and received on a bus to which the data transmitting and receiving apparatus is connected depending on the settings of the first information and the second information. Thus, a data transmitting and receiving apparatus that allows the functionality of the entire network to be improved can be accomplished.

The second aspect of the present invention is a data transmitting and receiving method for transmitting and receiving data between an external device and a pertinent bus of a plurality of buses connected by a bridge, the external device forming one portion of the bridge, the data transmitting and

receiving method comprising the steps of storing first
information and second information, the first
information representing whether the transmission
source or the transmission destination of the data is a
5 local device, the second information representing
whether or not to the data should be transmitted to the
pertinent bus and setting the first information and the
second information that have been stored to a
predetermined state corresponding to an external
10 request, and transmitting and receiving the data
to/from the pertinent bus or the external device
corresponding to the first information and the second
information that have been set. As a result, according
to the data transmitting and receiving method, data can
15 be transmitted and received in such a manner that a
local device is a transmission source or a transmission
destination without affecting data that is transmitted
and received on a bus to which the data transmitting
and receiving apparatus is connected depending on the
20 settings of the first information and the second
information. Thus, a data transmitting and receiving
apparatus that allows the functionality of the entire
network to be improved can be accomplished.

Although the present invention has been shown
25 and described with respect to a best mode embodiment
thereof, it should be understood by those skilled in
the art that the foregoing and various other changes,

omissions, and additions in the form and detail thereof may be made therein without departing from the spirit and scope of the present invention.